



## SolarEdge Single Phase Inverters

For North America

SE3000A-US / SE3800A-US / SE5000A-US / SE6000A-US /  
SE7600A-US / SE10000A-US / SE11400A-US



INVERTERS

### The best choice for SolarEdge enabled systems

- Integrated arc fault protection (Type 1) for NEC 2011 690.11 compliance
- Superior efficiency (98%)
- Small, lightweight and easy to install on provided bracket
- Built-in module-level monitoring
- Internet connection through Ethernet or Wireless
- Outdoor and indoor installation
- Fixed voltage inverter, DC/AC conversion only
- Pre-assembled AC/DC Safety Switch for faster installation
- Optional – revenue grade data, ANSI C12.1



# Single Phase Inverters for North America

SE3000A-US / SE3800A-US / SE5000A-US / SE6000A-US /  
SE7600A-US / SE10000A-US / SE11400A-US

	SE3000A-US	SE3800A-US	SE5000A-US	SE6000A-US	SE7600A-US	SE10000A-US	SE11400A-US		
<b>OUTPUT</b>									
Nominal AC Power Output	3000	3800	5000	6000	7600	9980 @ 208V 10000 @ 240V	11400	VA	
Max. AC Power Output	3300	4150	5400 @ 208V 5450 @ 240V	6000	8350	10800 @ 208V 10950 @ 240V	12000	VA	
AC Output Voltage Min.-Nom.-Max.* 183 - 208 - 229 Vac	-	-	✓	-	-	✓	-		
AC Output Voltage Min.-Nom.-Max.* 211 - 240 - 264 Vac	✓	✓	✓	✓	✓	✓	✓		
AC Frequency Min.-Nom.-Max.*	59.3 - 60 - 60.5 (with HI country setting 57 - 60 - 60.5)							Hz	
Max. Continuous Output Current	12.5	16	24 @ 208V 21 @ 240V	25	32	48 @ 208V 42 @ 240V	47.5	A	
GFDI	1							A	
Utility Monitoring, Islanding Protection, Country Configurable Thresholds	Yes								
<b>INPUT</b>									
Recommended Max. DC Power** (STC)	3750	4750	6250	7500	9500	12400	14250	W	
Transformer-less, Ungrounded	Yes								
Max. Input Voltage	500							Vdc	
Nom. DC Input Voltage	325 @ 208V / 350 @ 240V							Vdc	
Max. Input Current***	9.5	13	16.5 @ 208V 15.5 @ 240V	18	23	33 @ 208V 30.5 @ 240V	34.5	Adc	
Max. Input Short Circuit Current	30							Adc	
Reverse-Polarity Protection	Yes								
Ground-Fault Isolation Detection	600kΩ Sensitivity								
Maximum Inverter Efficiency	97.7	98.2	98.3	98.3	98	98	98	%	
CEC Weighted Efficiency	97.5	98	97.5 @ 208V 98 @ 240V	97.5	97.5	97 @ 208V 97.5 @ 240V	97.5	%	
Nighttime Power Consumption	< 2.5				< 4			W	
<b>ADDITIONAL FEATURES</b>									
Supported Communication Interfaces	RS485, RS232, Ethernet, ZigBee (optional)								
Revenue Grade Data, ANSI C12.1	Optional								
<b>STANDARD COMPLIANCE</b>									
Safety	UL1741, UL1699B, UL1998, CSA 22.2								
Grid Connection Standards	IEEE1547								
Emissions	FCC part15 class B								
<b>INSTALLATION SPECIFICATIONS</b>									
AC output conduit size / AWG range	3/4" minimum / 24-6 AWG				3/4" minimum / 8-3 AWG				
DC input conduit size / # of strings / AWG range	3/4" minimum / 1-2 strings / 24-6 AWG				3/4" minimum / 1-2 strings / 14-6 AWG				
Dimensions with AC/DC Safety Switch (HxWxD)	30.5 x 12.5 x 7 / 775 x 315 x 172		30.5 x 12.5 x 7.5 / 775 x 315 x 191		30.5 x 12.5 x 10.5 / 775 x 315 x 260			in / mm	
Weight with AC/DC Safety Switch	51.2 / 23.2		54.7 / 24.7		88.4 / 40.1			lb / kg	
Cooling	Natural Convection				Fans (user replaceable)				
Noise	< 25				< 50				dBA
Min.-Max. Operating Temperature Range	-13 to +140 / -25 to +60 (CAN version**** -40 to +60)							°F / °C	
Protection Rating	NEMA 3R								

\* For other regional settings please contact SolarEdge support.

\*\* Limited to 125% for locations where the yearly average high temperature is above 77°F/25°C and to 135% for locations where it is below 77°F/25°C.

For detailed information, refer to [http://www.solaredge.us/files/pdfs/inverter\\_dc\\_oversizing\\_guide.pdf](http://www.solaredge.us/files/pdfs/inverter_dc_oversizing_guide.pdf).

\*\*\* A higher current source may be used; the inverter will limit its input current to the values stated.

\*\*\*\* CAN P/Ns are eligible for the Ontario FIT and microFIT (microFIT exc. SE11400A-US-CAN).



# RoHS