







PV Powered[™] String Inverters



Proven Reliability – With Integrated AC and DC PV System Disconnect Listed to the UL 98 Standard

PV Powered String Inverters continue to deliver industry-leading reliability and technical innovations that lower the total cost of PV systems installation. Advanced Energy is now the only manufacturer of a string inverter-integrated AC/DC PV System Disconnect that is listed to the UL 98 Standard. The UL 98 Standard, called "Enclosed and Dead-front Switches," ensures the integrated PV Powered disconnect meets all installation and inspection requirements of a PV System Disconnect.

Housed within an NEC Compliant wire raceway, the innovative disconnect consists of one enclosure with generous working room for installation. In addition to providing for a single point of connection from the utility service and PV array, the wire raceway's optimized knockout locations also provide options for side, bottom and back entry with minimized conduit bending. The wire raceway enables flush side-by-side mounting, eliminating the need for extra equipment and resulting in a cleaner, less expensive installation.

The PV Powered string inverters are backed by the industry's first nation-wide ten year warranty and equipment replacement program. Optional performance monitoring is available which includes low cost, secure web-based access to inverter status and performance history.





- Endurance tested to 20 year operating life
- Lowest part counts and fewest interconnects eliminate common failure points
- Field-proven technology with thousands of units installed nationwide

Integrated AC and DC PV System Disconnect


- Listed to UL 98 Standard for use with PV Powered UL 1741 Listed string inverters
- Robust testing of switch mechanism to UL 98 Standard
- Single AC/DC switch visible and lockable in the OFF position
- NEC Compliant internal wire raceway enables side-by-side mounting
- Direct-to-wall surface enclosure design allows for easy access and installation

Easy Installation

- Factory integrated inverter and PV System Disconnect eliminates the need for extra equipment
- Integrated disconnect reduces conduit connection points saving installation time and material cost
- Field-configurable positive ground applications with simple jumper selection
- Optimally placed knockouts for a variety of conduit routing options

Installer-Focused Support

- No special purchase requirements to get the best technical support in the industry
- Live technical phone support
- Economical performance monitoring options



Example of Side-by-side Mounting on Standard Stud Spacing




20720 Brinson Boulevard PO Box 7348 Bend, OR 97708


1-541-312-3832 WWW.PVPOWERED.COM

DIMENSIONS


PVP2000 to PVP3500





UD SIANS NOCADOR VED GREAT 15 S/E 15



PVP4600, PVP4800, PVP5200









ELECTRICAL SPECIFICATIONS

MODEL	PVP2000	PVP2500	PVP2800	PVP3000	PVP3500	PVP4600	PVP4800	PVP5200		
Continuous Output Power (watts)	2000	2500	2800	3000	3500	4600	4800	5200		
Weighted CEC Efficiency (%)	92	94.5	92	93.5	95.5	95.5	96	96		
Maximum DC Input Voltage (VOC)	500	500	500	500	500	500	500	500		
DC Voltage Operating Range (V)	115-450	140-450	180-450	170-450	200-450	205-450	200-450	240-450		
DC Minimum Start Voltage (V)	130	155	195	185	215	220	215	255		
DC Maximum Current (A)	18.5	19	16.5	19	18.5	24	25.5	23		
AC Rated Output Current (A)	8.5	10.5	13.5	12.5	15	22.5	20.5	22		
AC Nominal Voltage (V)	240	240	208	240	240	208	240	240		
AC Output Voltage Range (V)	211-264	211-264	183-229	211-264	211-264	183-229	211-264	211-264		
AC Frequency Range (Hz)	59.3-60.5	59.3-60.5	59.3-60.5	59.3-60.5	59.3-60.5	59.3-60.5	59.3-60.5	59.3-60.5		

MECHANICAL SPECIFICATIONS

MODEL	PVP2000	PVP2500	PVP2800	PVP3000	PVP3500	PVP4600	PVP4800	PVP5200			
	Inverter with Factory-Integrated AC and DC PV System Disconnect										
	NEMA 3R Steel Enclosure, Wall Mounted with Bracket Included										
Temperature	-25°C to 40°C										
Weight (lbs) with Disconnect	92.5	106.5	106.5	106.5	120.5	162	162	162			
Inverter with Disconnect Dimensions	30 3/8" H x 15 5/8" W x 8 1/4" D	30 3/8" H x 15 5/8" W x 8 1/4" D	30 3/8" H x 15 5/8" W x 8 1/4" D		30 3/8" H x 15 5/8" W x 8 1/4" D	35" H x 18 1/8" W x 8 5/8" D		35" H x 18 1/8" W x 8 5/8" D			

AGENCY APPROVALS